

Return path included from 5 to 65 MHz. Shielded zamak chassis with plastic supports. F type connectors. Power supply jack, 9.5mm x 2.1mm. Distances of more than 75 m between multiswitch and outlet.

CODE	9130016				9130017			9130018		
MODEL		MU-130			MU-330			MU-630		
TV system		FM-TV / DVB-S / AM-TV / DVB-T								
Connection		F female								
Inputs		9								
Tap outputs		4			8			16		
Frequency range	MHz	5-862	950-2.150	2.150-2.500	5-862	950-2.150	2.150-2.500	5-862	950-2.150	2.150-2.500
Tap loss	dB±TOL	24 ±3,0	4 ±3,0	4 ±3,0	24 ±3,0	4 ±3,0	4 ±3,0	24 ±3,0	4 ±3,0	4 ±3,0
Tap equalization	dB	7	5	-	7	5	-	7	5	-
Flatness response	dB	±3,0								
Output level	dBµV	-	100 (IMD3 - 35 dB) 90 (IMD2 - 35 dB)		-	100 (IMD3 - 35 dB) 90 (IMD2 - 35 dB)		-	100 (IMD3 - 35 dB) 90 (IMD2 - 35 dB)	
Rejection between bands	dB	>25 TV/SAT >65 SAT/TV								
Isolation between bands	dB	>40 TV >30 SAT								