

# 943 NETWORK COMPONENTS

## UNIDENTIFIED RECEIVER FOR 1 DOOR

Code : **9430052**

Model : **CER-025**

### Description

CER-025 is the receiver station for radio messages coming from bracelets (CER-030) when the wanderer enters an area monitored by an activator (CER-010/CER-011). Once the message has been received, the station notifies its Wanderer Control Central associated the unit that a wanderer entered the monitored area. The receiver station includes a potential free contact (NO) that is closed as long as the wanderer remains in the monitored area, to be able to close a door, activate a siren, etc. This contact remains activated 30 seconds after the wanderer has left the area being monitored. The maximum distance between CER-025 and bracelet is 100 m outdoors. The maximum number of bracelets that can be registered to one CER-025 receiver is 500.

9430052

CER-025

### Especificaciones

Frecuencia	868 MHz
Alimentación	220 Vac 50 Hz
Número de relés de salida	3 (1 para control de desincronización. 2 libres para control de salidas externas (sirena, señalizador luminoso, abrepuertas, etc.)
Temperatura de funcionamiento	De -20 a - 85°C
Estanqueidad	IP54(con prensaestopa IP65)
Dimensiones	215 x 150 x 70 mm
Área de activación	100 m