

941

SENSORS AND ACTUATORS

BED UNIT CALL & MAGNETIC CONNECTOR

Code : **9415064**

Model : **LLC-861**

Bed unit with 1 button (call) and socket for connecting call handset (Magnetic)



| CÓDIGO-CODE-CODE | 9415064 | 9415062 | 9415063 |
|--|---|---|---|
| MODELO-MODEL-MODÈLE | LLC-861 | LLC-862 | LLC-863 |
| Botones Buttons Boutons | Llamada de enfermera Nurse call Bouton d'appel | Llamada de enfermera + Presencia Nurse call + Presence Bouton d'appel + Presence | Llamada de enfermera + Presencia + Llamada azul Nurse call + Presence + Blue call Bouton d'appel + Presence + Blue appel |
| Luces Lights Lumières LED | 1 | 2 | 3 |
| Alimentación Power supply Alimentation | 24Vdc | | |
| Consumo Consumption Consommation | 60mA | | |
| Tensión control de luces Light control power supply Alimentation pour contrôle d'éclairage | 5Vdc (ACC-421) | | |
| Conector Connector Connecteur | Magnético hembra Magnetic female Magnétique femelle | | |
| Índice de protección Protection index Indice de protection | IP42 | | |
| Dimensiones Dimensions Dimensions | 80x80x30mm | | |
| Peso Weight Poids | 80gr | | |

TABLAS DE CONEXIONADO / CONNECTION BOARDS / TABLES DE CONNEXIONS

| | ES | EN | FR | Producto |
|----|----------------------|---------------------|--------------------|-------------------------|
| A1 | Luz roja | Red light | Lumière rouge | LLC-861/LLC-862/LLC-863 |
| A2 | Pulsador de llamada | Call button | Bouton d'appel | LLC-861/LLC-862/LLC-863 |
| A3 | GND | GND | Masse | LLC-861/LLC-862/LLC-863 |
| A4 | Alimentación 24 V | Power supply 24 V | Alimentation 24V | LLC-861/LLC-862/LLC-863 |
| B1 | C1 | C1 | C1 | ACC-421 |
| B2 | C2 | C2 | C2 | ACC-421 |
| B3 | C3 | C3 | C3 | ACC-421 |
| B4 | C4 | C4 | C4 | ACC-421 |
| C1 | Luz verde | Green light | Lumière verte | LLC-862/LLC-863 |
| C2 | Pulsador presencia | Precece button | Bouton de présence | LLC-862/LLC-863 |
| C3 | Luz código azul | Blue code light | Lumière code bleue | LLC-863 |
| C4 | Pulsador código azul | Blue code button | Code bouton bleu | LLC-863 |
| D1 | Luz roja pera | Handset red light | LED rouge poire | LLC-861/LLC-862/LLC-863 |
| D2 | Pulsador de pera | Handset push button | Poire d'appel | LLC-861/LLC-862/LLC-863 |

