943 NETWORK COMPONENTS

DETECTION BRACELET

Code : **9430046**

Model : **CER-030**

Description
Bracelet worn by the resident. When the wanderer enters an area monitored by an activator (CER-010/CER-011), the bracelet indicates the presence of the person in the area sending a Radio message to the preset Receiver station. When the wanderer enters the range of the activator (CER-010/CER-011), the bracelet is continuously transmitting to the Receiver station as long as the person remains within the range of the activator to alert of his presence in the area. Out of the activator range, the bracelet remains in standby. Maximum distance between bracelet and receiver is 100 m outdoors.

9430046	
CER-030	
Especificaciones	
Frecuencia de trabajo	125KHz (activación) 868 MHz (emisión)
Alimentación	Pila de 3V (CR2032)
Tiempo de vida de la batería	1 año aproximadamente (se recomienda revisión casa 6 meses)
Control de batería	Nivel óptimo: LED brilla durante la transmisión Nivel bajo: LED brilla débilmente o no brilla durante la transmisión.
Temperatura de operación	De -20ºC to 55ºC
Dimensiones (anchura x altura x profundidad)	47 x 35 x 11mm
Material	Policarbonato
Color	Negro translucido
Índice de protección	IP65