

979 HOME AUTOMATION

IPAL WIRELESS MOTION PIR SENSOR

Code : **9790013**

Model : **WSN-400**



Wireless RF motion sensor. Battery operated and has a range of 9-12m and 110°

Its great functionalities are not at odds with its sophistication: the range of digital home devices compatible with the IPAL system makes it possible to quickly and easily convert any home into a modern and elegant digital home: lighting control mechanisms, curtains and blinds; smoke or motion sensors; smart plugs and save energy. Its glass-like finish, in white, underlines a discreet design that combines with any decoration. The capacitive keyboard, by reducing the possibility of mechanical failure, prolongs its useful life while facilitating its cleaning.

CÓDIGO-CODE-CODE		9790013
MODELO-MODEL-MODÈLE		WSN-400
Función Function Fonction		Sensor de movimiento PIR PIR motion sensor Décteur de mouvement PIR
Materiales Materials Matériau		ABS
Color Colour Couleur		Blanco White Blanc - Noir
Nº pulsadores No. buttons Nº boutons poussoirs		1 (Test)
Comunicación Communication Communication	MHz	RF Banda 433 RF Band 433 RF Bande 433
Alarma Alarm Alarme		Por RF Via RF Pour RF
Área de detección Detection area Aire de détection	m	9-12
Ángulo de detección angle of detection angle de détection	Deg	110 °
Alimentación Power supply Alimentation	Vdc	Batería 6F22 de 9Vdc 6F22 battery, 9Vdc Batterie 6F22 de 9Vdc
Montaje Installation type Montage		De superficie, orientable Surface mounted, adjustable En saillie, orientable
Temperatura de funcionamiento Temperature range Température de fonctionnement	°C	-10 ,,, +50
Dimensiones exteriores Dimensions Dimensions extérieures	mm	106 x 62 x 46