941 SENSORS AND ACTUATORS

BED UNIT CALL,PRESENCE,BLUE,MAGNETIC



Code : **9415063**

Model : **LLC-863**

Description:
Touch-operated bed unit with three buttons (call, presence and code blue), magnetic connector compatible with LLC-77x call handsets and three reassurance LEDs, one for each button. Easy to clean thanks to the antibacterial coating on its front panel. A call can be initiated using the red call button, presence can be registered using the green button and a code blue can be activated using the corresponding button. Both the red and blue LEDs indicate the status of the corresponding call. Flush-mounted or surface-mounted installation.

CÓDIGO-CODE-CODE	9415064	9415062	9415063
MODELO-MODEL-MODÈLE	LLC-861	LLC-862	LLC-863
Botones Buttons Boutons	Llamada de enfermera Nurse call Bouton d´appel	Llamada de enfermera + Presencia Nurse call + Presence Bouton d´appel + Presence	Llamada de enfermera + Presencia + Llamada azul Nurse call + Presence + Blue call Bouton d´appel + Presence + Blue appel
Luces Lights Lumières LED	1	2	3
Alimentación Power supply Alimentation	24Vdc		
Consumo Consumption Consommation	60mA		
Tensión control de luces Light control power supply Alimentation pour contrôle d'éclairage	5Vdc (ACC-421)		
Conector Connector Connecteur	Magnético hembra Magnetic female Magnétique femelle		
índice de protección Protection index Indice de protection	IP42		
Dimensiones Dimensions Dimensions	80x80x30mm		
Peso Weight Poids	80gr		

TABLAS DE CONEXIONADO / CONNECTION BOARDS / TABLES DE CONNEXIONS				
	ES	EN	FR	Producto
A1	Luz roja	Red light	Lumière rouge	LLC-861/LLC-862/LLC-863
A2	Pulsador de llamada	Call button	Bouton d´appel	LLC-861/LLC-862/LLC-863
A3	GND	GND	Masse	LLC-861/LLC-862/LLC-863
A4	Alimentación 24 V	Power supply 24 V	Alimentation 24V	LLC-861/LLC-862/LLC-863
B1	C1	C1	C1	ACC-421
B2	C2	C2	C2	ACC-421
B3	C3	C3	C3	ACC-421
B4	C4	C4	C4	ACC-421
C1	Luz verde	Green light	Lumière verte	LLC-862/LLC-863
C2	Pulsador presencia	Precence button	Bouton de présence	LLC-862/LLC-863
C3	Luz código azul	Blue code light	Lumière code bleue	LLC-863
C4	Pulsador código azul	Blue code button	Code bouton bleu	LLC-863
D1	Luz roja pera	Handset red light	LED rouge poire	LLC-861/LLC-862/LLC-863
D2	Pulsador de pera	Handset push button	Poire d´appel	LLC-861/LLC-862/LLC-863

